

30% Smaller & Lighter
Faster GPS Acquisition
Improved Message Transmission

SPOT Features Comparison

www.findmespot.com



New

SPOT Satellite GPS Messenger



SPOT Satellite Personal Tracker

	SPOT 2	SPOT 1
FEATURES		
Standby Mode	94.7 days*	365 days*
Check- In/Ok (sends 3x Every 5min for 15 min)	350 msg max*	650 msg max*
Help (sends every 5min for 1 hr)	with Button Cover - 810 msg max*	1950 msg max*
Emergency (sends every 5 min Until Battery Dies)	S.O.S. with Button Cover - 810 msg max (2.8 days)*	911 - 1950 msg max (7days)*
Tracking (sends every 10 min for 24 hrs)	Independent Button - 625 msg max (4.3 days)*	1950 msg max (14 days)*
Tracking Message Queing	transmits Current +2 Previous*	No
Replaceable Help/ Emergency Button Covers	Yes	No
GPS LED Indicator	Yes	No
Message Sending LED Indicator	Yes	No
Custom Message (sends 3x Every 5min for 15 min)	350 msg max*	No
Universal Icons	Yes	No
Standard Carrying Case Included	Yes	No
Carabineer	Yes	No
SPECIFICATIONS		
Weight	5.2 oz - 30% Lighter	7.37 oz
Size	3.7" x 2.6" x 1" - 30% Smaller	4.38" x 2.75" x 1.75"
GPS Acquisition	≤ 1 min Typical	<1 to 15 min
GPS Chipset	New GPS chip increased sensitivity & improved performance uBlox AMY-5M Almanac Data Needed = No No Need for Calibration	Nemerix NB1030 Almanac Data Needed = Yes Calibration Needed if not Used in 2 wks or if moved > 965kms
Antenna	Axonn (Improved antenna for faster GPS acquisition & message transmission)	Spectrum
Certifications	FCC, IC, CE	FCC, IC, CE, C-Tick, Anatel
Intrinsic Safety	Intrinsic Safety UL913 & CSA C22.2 No. 157 (Target Jan. Y10)	No
Power	3 AAA Ultimate Lithium Energizer L92 Batteries	2 AA Ultimate Lithium Energizer L91 Batteries
OPERATING CONDITIONS		
Waterproof	5 metres for 1 hour	1 metre for 30 mins.
Temperatures	-30C to + 60C	-40C to + 85C
Altitude	-100 m to + 6,500 m	-91 m to + 6,492 m
Shock Resistant	Yes	Yes
Humidity and Salt Fog Rated	Yes	Yes
WARRANTY		
Unit	1-Yr Limited Warranty	1-Yr Limited Warranty
SPOT ORDERING CODE	Spot2-0-CA - (UPC 893049001219)	Spot1B (UPC 893049001059)

*Under normal usage a full battery should meet or exceed these amounts.